

Digital Jobsite Radio



DMR110



Product Objectives

- Update our range of portable jobsite radios so that they are compatible with 18V LXT, 14.4V LXT, 12V MAX CXT, 10.8V and 7.2V Li-ion batteries
- Expanding the Makita jobsite radio range, a must have for every jobsite, campsite and backyard



DMR105



DMR110

Product Overview





Power source:	AC or Makita Li-ion batteries
Frequency Band	FM: 87.5 – 108 DAB+: 174.928 – 239.200
Digital audio	Yes
Input jack	AUX-IN x2
Speaker	∅76mm x2
Weight	4.0kg

- **Flexible antenna** – can be folded and protected underneath the carry handle or removed and stored inside the battery compartment
- **Durable design** – front metal pipe and elastomer bumpers protect against rough handling with falling impact strength of 1.0m
- **Digital audio** – capable of receiving DAB+
- **AUX-IN jack** – can be used as a stereo speaker by connecting an external audio source via 3.5mm AUX cable
- **Dust and shower proof construction** – IP64 rated for use in outdoor applications
- **2 speaker stereo** – two large speakers provide high quality sound
- **AC adapter jack** – user has the option to power the unit by Makita Li-ion batteries or AC power via the supplied AC adapter

Design



Light weight and compact design make Makita radios a favourite on the jobsite

Durability



IP64 rated for use in harsh environments and a fall impact strength of 1.0m

Quality









Large diameter speakers provide high quality sound

Convenience



Powered by Makita 7.2V to 18V Li-ion batteries or AC adapter

Jobsite Radio Features

		Bluetooth	USB Output *For charging mobile devices	DAB+ Digital Radio	AUX-IN
DMR110		✗	✗	✓	✓
DMR108		✓	✓	✗	✓
DMR107		✗	✗	✗	✓
DMR106		✓	✓	✗	✓
DMR105		✗	✗	✓	✓
DMR102		✗	✗	✗	✓

Dust and shower proof construction

The IP rating or ingress protection rating is an international standard that classifies the degrees of protection a product can withstand from solid objects like dust and water. The first digit indicates protection against solids and the second digit against liquids.

All jobsite radios (excluding the BMR050) are IP64 rated meaning protection from total dust ingress and protected from water spray from any direction



Identifying the difference

The DMR110 has been modelled on the DMR105 and is equipped with the same features, however there are two identifying marks that allow identification between the two. The centre part of the turning dial on the DMR105 is grey while on the DMR110 it is black. The second feature is on the side of the housing as there is a CXT logo next to the LXT logo



DMR105 – Grey dial



DMR110 – Black dial



DMR105 – Housing



DMR110 – Housing

Accessories



Standard Equipment



SE00000306

AC adaptor

Optional Equipment



BL1815N to
BL1860B

18v Li-Ion Batteries
BL1815N 1.5Ah to BL1860B 6Ah



DC18RC

240V Fast Charger



DC18SD

240V Standard
Charger



DC18RD

Dual Port Rapid
Charger